

## SmartOnline S3MT-Series 3-Phase 60kVA Input Isolation Transformer, 600V Delta to 208V Wye

MODEL NUMBER: **S3MT-60K600V**



60kVA/kW transformer provides 600V (Delta) to 208V (Wye) step-down and isolation protection to a 3-phase UPS and its load.

### Features

#### Get Complete Step-Down/Step-Up and Isolation Protection

Tripp Lite's S3MT-60K600V 60kVA/kW transformer offers line isolation and protection to the connected 3-phase UPS system and its load. It isolates the UPS and connected components from line surges and spikes caused by utility power disruptions that can damage equipment or corrupt data. The step-down input isolation transformer is ideal for 4-wire (3Ph+N+PE) IT loads in government, manufacturing, healthcare and corporate settings with a 600V electrical feed and 208/120V equipment.

#### Performs with High Efficiency up to 97.5%

Not only is the S3MT-60K600V very efficient, with up to 97.5 percent efficiency, but it is also very quiet with a noise profile less than 65 dBA. A built-in circuit breaker on the output side helps prevent dangerous power overloads. Four ball-bearing cooling fans help prevent overheating. An overheat-sensing relay and switch combine with a red LED indicator to provide over-temperature warning and overheating protection.

#### Small Footprint for Quick Installation in a Compact Space

The compact footprint enables installation of the S3MT-60K600V with minimal space. The rugged stainless steel housing ships ready for immediate tower installation with a compatible 50–60kVA/kW Tripp Lite S3M-Series 208V 3-phase UPS system.

### Highlights

- Recommended for government, manufacturing, healthcare and corporate settings
- Up to 97.5% efficiency with a quiet acoustic profile less than 65 dBA
- Resettable protection relay/switch and red LED indicator warn against overheating
- Rugged stainless steel housing with compact footprint comes ready for installation
- Compatible with 50–60kVA/kW Tripp Lite S3M-Series 208V 3-phase UPS systems

### Applications

Protect healthcare, manufacturing, industrial, corporate and other IT equipment where the upstream power source is 600V and the load requires a 208V 3-phase UPS

### System Requirements

50–60kVA/kW Tripp Lite S3M-Series 208V 3-phase UPS system

### Package Includes

- S3MT-60K600V 3-Phase 60kVA Input Isolation Transformer
- (4) Bottom skirts
- (24) Screws
- Owner's manual

## Specifications

OVERVIEW	
UPC Code	037332253163
Efficiency	96.5% @ full load
Nominal Voltage / Frequency	600V 3-PH / 60Hz
VA / Watt Capacity	60000



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

Transformer Type	Dry type, Input step-down isolation transformer
<b>INPUT</b>	
Nominal Input Voltage(s) Supported	600V 3-PH Delta
UPS Input Connection Type	Hardwire
Input Phase	3-Phase
<b>OUTPUT</b>	
Output Volt Amp Capacity (VA)	60000
Output Capacity (kVA)	60
Output Receptacles	Hardwire
<b>PHYSICAL</b>	
Primary Form Factor	Tower
Cooling Method	4x BALL BEARING, 120MM (576 TOTAL CFM)
Form Factors Supported	Tower
Shipping Dimensions (hwd / in.)	55.10 x 27.60 x 37.80
Shipping Weight (kg)	407.78
Unit Dimensions (hwd / in.)	47.2 x 23.6 x 33.5
Unit Dimensions (hwd / cm)	120 x 60 x 85
Unit Weight (lbs.)	789
Unit Weight (kg)	357.88
<b>ENVIRONMENTAL</b>	
Heat Dissipation (BTU/Hr) @ Full Load	7167
<b>INPUT TRANSFORMER</b>	
Input Voltage	600V
Input Voltage Range	(-45%, +25%) for 40% load (-20%, +25%) for 100% load
Input Amp(s)	81 A
AC Input Configuration	Delta
AC Input Frequency	50/60
Frequency Range	40/70Hz
Voltage Selection	NONE
Input Inrush Current	710 A
VA Rating	60K
Input Number of Phases	3PH



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

AC Output Voltage (V)	600 V
AC Output Amps	225 A
Output Number of Phases	3PH + N
AC Output Configuration	WYE
Output Isolation	Yes
Output Breaker Rating	250 A
Connection Type	COPPER BAR
LED Warning Light Functions	The over-temperature warning LED light will turn ON when the output/secondary of the Input transformer reaches 160°C ±5°C and will turn OFF when the corresponding transformer cools down to 125°C ±5°C
Over Temperature Reset	
Efficiency @ Half Load	97.5%
Efficiency @ Full Load	96.5%
Heat Dissipation (BTU/Hr) @ Full Load	7167
Audible Noise (dBA @ 1m)	65dB max
<b>WARRANTY</b>	
Product Warranty Period (Worldwide)	2-year limited warranty
Product Warranty Period (U.S. & Canada)	2-year limited warranty

© 2021 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <https://www.tripplite.com/products/product-certification-agencies>