

# Single Channel Linear DC Power Supply

## MPS-H-1C Series



- It can save the output status and value before the last shutdown
- Current can be pre-set without short circuit;
- Current and voltage output can be set in a certain range, which can prevent misoperation from damaging the tested object
- Slow startup circuit design, small surge current

- Voltage compensation function to ensure high precision
- Two groups memory, can be recalled quickly
- One click to restore factory settings

Standard SENSE

Interface RS232 RS485 USB

### ≤600W Linear DC power supply

Model	Voltage	Current	Power
MPS-3010H-1	0~30V	0~10A	300W
MPS-3020H-1	0~30V	0~20A	600W
MPS-6005H-1	0~60V	0~5A	300W
MPS-6010H-1	0~60V	0~10A	600W
MPS-10003H-1	0~100V	0~3A	300W
MPS-20002H-1	0~200V	0~2A	400W
MPS-30001H-1	0~300V	0~1A	300W

Model	MPS-3010H-1C	MPS-3020H-1C	MPS-6005H-1C	MPS-6010H-1C	MPS-10003H-1C	MPS-20002H-1C	MPS-30001H-1C
<b>Input voltage</b>							
Rated output	Voltage 0~30V	Voltage 0~30V	Voltage 0~60V	Voltage 0~60V	Voltage 0~100V	Voltage 0~200V	Voltage 0~300V
	Current 0~10A	Current 0~20A	Current 0~5A	Current 0~10A	Current 0~3A	Current 0~2A	Current 0~1A
Load regulation rate	Voltage ≤0.01%+10mV	Voltage ≤0.01%+10mV	Voltage ≤0.01%+5mV	Voltage ≤0.01%+5mV	Voltage ≤0.01%+8mV	Voltage ≤0.01%+12mV	Voltage ≤0.01%+12mV
	Current ≤0.2%+5mA						
Line regulation rate	Voltage ≤0.01%+10mV	Voltage ≤0.01%+10mV	Voltage ≤0.01%+5mV	Voltage ≤0.01%+5mV	Voltage ≤0.01%+8mV	Voltage ≤0.01%+12mV	Voltage ≤0.01%+12mV
	Current ≤0.2%+5mA						
Setting resolution rate	Voltage 1mV	Voltage 1mV	Voltage 1mV	Voltage 1mV	Voltage 10mV	Voltage 10mV	Voltage 10mV
	Current 1mA						
Setting accuracy	Voltage ≤0.01%+10mV	Voltage ≤0.01%+10mV	Voltage ≤0.01%+10mV	Voltage ≤0.01%+10mV	Voltage ≤0.01%+80mV	Voltage ≤0.01%+80mV	Voltage ≤0.01%+80mV
	Current ≤0.1%+5mA	Current ≤0.1%+10mA	Current ≤0.1%+5mA	Current ≤0.1%+5mA	Current ≤0.1%+5mA	Current ≤0.1%+5mA	Current ≤0.1%+5mA
Readback resolution rate	Voltage 1mV	Voltage 1mV	Voltage 1mV	Voltage 1mV	Voltage 10mV	Voltage 10mV	Voltage 10mV
	Current 1mA						
Readback accuracy	Voltage ≤0.01%+10mV	Voltage ≤0.01%+10mV	Voltage ≤0.01%+10mV	Voltage ≤0.01%+10mV	Voltage ≤0.01%+80mV	Voltage ≤0.01%+80mV	Voltage ≤0.01%+80mV
	Current ≤0.1%+5mA	Current ≤0.1%+10mA	Current ≤0.1%+5mA	Current ≤0.1%+5mA	Current ≤0.1%+5mA	Current ≤0.1%+5mA	Current ≤0.1%+5mA
Ripple and noise	Voltage ≤3mV(rms)						
	Current ≤5mA(rms)						
Working temperature	0~40°C≤80%RH						
Size (WxHxD)	cm	250*150*330					
Weight	kg	8	13	8	13	12	12
Interface		RS-232, RS-485, USB					